
Support Units - Fixed Side, Square

Standard

Points of comparison between similar products | Consider using these parts when the usage environment is high-load application and high operation frequency.



Part Number		Support																	Oil Seal
Туре	No.	Side SET	d	L	L ₁	L2	Lз	В	Н	h	B ₁	H ₁	Р	d1	d2	l	M (Fine)	Т	Applicable Shaft Dia.
	6	-SET (Only when purchasing in Sets)	6	20	-	22.5	3.5	42	25	13	18	20	30	5.5	9.5		M6x0.75	12	-
	8 S		8	23		26	4	52	32	17	7 25	26	38 6.6	66	3 11		M8x1.0	14	10
	8			23 -	_				32	17	23	20		0.0				14	11.5
	1022		10				6 6	70	40	22		32				11	M10x1.0 17		14
	10S				6	29.5			43	25		35			14	11		17	12
BSW	10			24									52	9					14
BSWN	1223		12	,					41	23		33				M12x1.0	19	15	
BSWR	12		12						43	25		35	j				WIIZXI.U	13	10
	1526		15	25				80	46	26		36			17				
	1528				6	38			48	28	41	38	60	11		15	M15x1.0	22	20
	15								50	*30		40		''	17	13			
	20			42	10	52		95	58		56	45	75				M20x1.0	30	25
	25		25	48	13	59	14	105	68	35	66	25	85	11	-	-	M25x1.5	35	31

Take care in combining No.20 with Ball Screw BSSZ(K)2510, BSSR(K)2510 or BSST2510. The ball screw nut may come in contact with the bottom surfaces.



Part Number

BSW15 (Fixed-side single type)

BSW15-SET (SET part type)


For details of Bearings in addition to mounting interface accuracies of Support Units, Included Collar and Bearing Nut, see EP.759

 Ball Screw Compatibility Chart ► P.756 The store Accessories with care since they are required when assembling.

Type	No.	Unit Price	Unit Price				
Type	INO.	1 ~ 10 pc(s).	1 ~ 10 pc(s).	1 ~ 10 pc(s).	1 ~ 10 pc(s).	1 ~ 10 pc(s).	1 ~ 10 pc(s).
	6						
	8 S						
	8						
BSW	1022						
BSWN	10S						
BSWR	10						
BSW-SET	1223						
BSWN-SET	12						
	1526						
BSWR-SET	1528						
	15						
	20						
	25						

Part Number BSW BSW-SET BSWN BSWN-SET BSWR BSWR-SET

Support Units - Support Side, Square < Standard> Standard




Part Num	ber														D	BUN	BUNM	BUNR
Туре	No.	d	L	В	H	h	B ₁	H ₁ P	Р	V	d1	d2	l	Bearing Type	Retaining Ring	Unit Price	Unit Price	Unit Price
Type	110.														9	1 ~ 10 pc(s).	1 ~ 10 pc(s).	1 ~ 10 pc(s).
	6	6	12	12 42	25	13	18 20 30	30	17	, 5.5	9.5	44	B606ZZ STW	STWN, S6				
	8	0	15	52	32	17	25	26	38	17	6.6	11	11	DOUGZZ	31 WIV, 30			
	1022	8			40	22		21		22		0		B608ZZ	STWN, S8			
BUN	10	8		70	43	25	36	24	52					DOUGLE				
	1223	10		70	41 2	23	22 24	52	26	9			B6000ZZ	STWN, S10				
BUNM	12)	43	25							DOUUUZZ					
BUNR	1526				46	26		21			11	-	-		STWN, S15			
	1528	15		80	48	28	41	23	60	32				B6002ZZ				
	15				50	*30		25										
	20	20	20 26 95		58	30	56	30	75	47				B6204ZZ	STWN, S20			
	25	25	30	105	68	35	66	25	85	52				B6205ZZ	STWN, S25			

Take care in combining No.20 with Ball Screw BSSZ(K)2510, BSSR(K)2510 or BSST2510. The ball screw nut may come in contact with the bottom surfaces.



Example BUN15 (Support side, separate item)



<SET parts>

BSW25-SET

Black Oxide							
SET Part	SET parts						
Number	Fixed Side Part Number	Support Side Part Number					
BSW6-SET	BSW6	BUN6					
BSW8S-SET	BSW8S	BUN8					
BSW8-SET	BSW8	BUN8					
BSW1022-SET	BSW1022	BUN1022					
BSW10S-SET	BSW10S	BUN10					
BSW10-SET	BSW10	BUN10					
BSW1223-SET	BSW1223	BUN1223					
BSW12-SET	BSW12	BUN12					
BSW1526-SET	BSW1526	BUN1526					
BSW1528-SET	BSW1528	BUN1528					
BSW15-SET	BSW15	BUN15					
BSW20-SET	BSW20	BUN20					

BUN25

BSW25

Electroless Nickel Plating								
SET Part	SET parts							
Number	Fixed Side Part Number	Support Side Part Number						
BSWN6-SET	BSWN6	BUNM6						
BSWN8S-SET	BSWN8S	BUNM8						
BSWN8-SET	BSWN8	BUNM8						
BSWN1022-SET	BSWN1022	BUNM1022						
BSWN10S-SET	BSWN10S	BUNM10						
BSWN10-SET	BSWN10	BUNM10						
BSWN1223-SET	BSWN1223	BUNM1223						
BSWN12-SET	BSWN12	BUNM12						
BSWN1526-SET	BSWN1526	BUNM1526						
BSWN1528-SET	BSWN1528	BUNM1528						
BSWN15-SET	BSWN15	BUNM15						
BSWN20-SET	BSWN20	BUNM20						

BUNM25

BSWN25-SET BSWN25

Low Temperature Black Chrome Plating								
SET Part	SET parts							
Number	Fixed Side Part Number	Support Side Part Number						
BSWR6-SET	BSWR6	BUNR6						
BSWR8S-SET	BSWR8S	BUNR8						
BSWR8-SET	BSWR8	BUNR8						
BSWR1022-SET	BSWR1022	BUNR1022						
BSWR10S-SET	BSWR10S	BUNR10						
BSWR10-SET	BSWR10	BUNR10						
BSWR1223-SET	BSWR1223	BUNR1223						
BSWR12-SET	BSWR12	BUNR12						
BSWR1526-SET	BSWR1526	BUNR1526						
BSWR1528-SET	BSWR1528	BUNR1528						
BSWR15-SET	BSWR15	BUNR15						
BSWR20-SET	BSWR20	BUNR20						
BSWR25-SET	BSWR25	BUNR25						